



PHS-06A PHOTO ELECTRIC CONTROLLER

PHS-06A-1
PHOTO ELECTRIC
CONTROLLER

PHS-06A-2
SOCKET



REMARK:

- PHS-06A (PHOTO ELECTRIC CONTROLLER WITH SOCKET)
- PHS-06A-1 (PHOTO ELECTRIC CONTROLLER ONLY)
- PHS-06A-2 (SOCKET ONLY)

Introduction:

PHS-06A is designed for automatic light control. It can be used to turn on streetlights at night and turn off at dawn.

Safety Precaution:

Any improper use of this product can cause short circuit, which can damage product itself or even cause fire. Please read instruction carefully and make sure:

1. Wiring and mounting position are correct according to instruction.
2. Auto lighter must work within rated current and voltage.

Technical Data:

- 1) Rated voltage: 105-305VAC
- 2) Rated frequency 50-60Hz
- 3) Current: 10A,
- 4) Max Load: 1000W, 1800VA
- 5) Working Environment: 32 122°F (0°F-50°F)
- 6) Acting time:
 - Turn on in 30 seconds when light level $\leq 10\text{Lux}$
 - Turn off in 2 minutes when light level $\geq 70\text{Lux}$
- 7) Specification:
 - Weight: 220g
 - Size: 110mm x 90mm x 85mm

Installation:

- 1) Install with sensor face up to the sky as show in picture
- 2) Window on the sensor should not face potential light sources
- 3) Connect wires to circuit as following:
 - Load: Red wire
 - Common: White wire
 - Source: Black wire
- 4) Mount light sensor to supporting structure with metal support included.

